

**The BCD536HP WiFi and SDS200 LAN RTSP audio allows only one application at a time to connect to the scanner LAN RTSP.**

**MediaMTX Media Server overcomes this limitation.**

<https://github.com/bluenviron/mediamtx>

Instead of ProScan and RadioFeed connected directly to the scanner RTSP audio, ProScan and RadioFeed connects to the MediaMTX server and the MediaMTX server connects to the scanner.

### **Setup:**

1. Download here: <https://sourceforge.net/projects/rtspserver.mirror/>  
*It shows as RtspSimpleServer because it was renamed to MediaMTX*
2. Unzip and copy to a new folder
3. Edit the mediamtx.yml file  
paths:  
sds200:  
source: rtsp://192.168.254.22/au:scanner.au  
  
bcd536hp:  
source: rtsp://192.168.254.32/au:scanner.au  
  
{substitute scanner IP address}
4. At the command prompt, run mediamtx.exe
5. In ProScan/RadioFeed, in the Audio URL Setup box, input  
rtsp://192.168.254.11:8554/sds200  
{substitute computer running MediaMTX IP address}

That's it!